

Signal Converter

CVI to HDMI & VGA Converter

CVI - ER03



Description Features:

- * Support all type CVI resolution: D1, 960H, 720P, 1080P
- * HDMI resolution: 720P, 1080I, 1080P25/30/50/60
- * VGA output support 720P, 1080P
- * User selectable output format (HDMI and VGA) by the buttons

Our CVI to HDMI & VGA Converter is designed to convert one channel CVI video source to HDMI & VGA displays simultaneously.

It supports multiple resolutions up to 720P, 1080P and supports the most popular resolutions to ensure high compatibility with wide brands of PC and HDTV. It provides cheaper solution to connect CVI to HDTV and VGA terminal

Specification	CVI-ER03
Model	CVI to HDMI & VGA converter
Input Interface	1x BNC
Input Signal Type	1X CVI
Support Input Format	D1 ,960H, 720P, 1080P
Video Signal Range	0.8V p-p
Video Impedance	75 ohms
Max. Input Coax Length	500meter for 720p
HDMI/DVI Output	1x HDMI ,2X CVI output
HDMI format	720p,1080i, 1080P25/30/50/60
VGA Output	1x VGA
VGA format	720P ,1080P
AV (CVBS) output	1 x BNC -F
Power Supply	DC12V,1A
Power Consumption	4-5Watts
Operating Temperature	-10°C ~ 60°C / 14°F ~ 140°F
Storage Temperature	-30°C ~ 70°C / -22°F ~158°F
Relative Humidity	20~90% RH (Non-condensation)
Dimension	128*84*26mm